

Features

- Inherently Matched LED Current driver chip
- High Efficiency:83%
- Drives Up to Five LEDs from 2.2V Supply
- 17V Over Voltage Protection
- Fast 1.4MHz Switching Frequency
- Requires Only 1 μ F Output Capacitors
- SOT-23-6 Package

Applications

- Communication equipment
- White LED Backlight Display for PDA
- Pocket PC
- Handheld Devices
- GPS, portable DVD, digital-frame
- White LED display backlighting


General Description

The BM0123A is a step-up DC/DC converter specifically designed to drive up to 5 series white LEDs with constant current. Series connection of the LEDs provides identical LED currents resulting in uniform brightness and eliminates the need for ballast resistors. The BM0123A switches at 1.4MHz, allowing the use of tiny external components. A low 0.255V feedback voltage minimizes power loss in the current setting resistor for high efficiency. The OVP pin monitors the output voltage and turns off the converter whenever the LEDs are open. The BM0123A is available in low profile SOT-23-6 package.


It can drive up to 5 (series) * 9 (parallel) LEDs

Pin to pin with RT9271 and AIC1896


Block Diagram



Pin Assignment



Typical Application Circuit



Absolute Maximum Ratings

Input Voltage	6V
OVP Voltage.....	36V
FB Voltage	6V
SW Voltage.....	36V
<u>SHDN</u> Voltage	6V
Storage Temperature	-40°C to 125°C

Note: These are stress ratings only. Stresses exceeding the range specified under “Absolute Maximum Ratings” may cause substantial damage to the device. Functional operation of this device at other conditions beyond those listed in the specification is not implied and prolonged exposure to extreme conditions may affect device reliability.

Electrical Characteristics

$V_{EN}=4.0V$; $V_{IN}=4.0V$; $T_a=25^\circ C$

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Input Voltage	V_{in}	--	2.2	4.0	5.5	V
Feedback Voltage	V_{SHDN}	$I_{out}=20\text{ mA}, 3LED$	210	255	265	mV,
Switching Frequency	FSW	$I_{out}=20\text{ mA},$	1.1	1.45	1.5	MHz
SHDN Voltage High	V_H	--	1.3	--	--	V
SHDN Voltage Low	V_L	--	--	--	0.8	V
OVP Voltage	V_{ovp}	--	--	20	--	V
ICC1		$V_{in}=3V, V_{en}=GND$		0.005		uA
ICC2		$V_{in}=5V, V_{en}=GND$		0.006		uA
ICC3		$V_{in}= V_{en}=3V$		1		mA
ICC4		$V_{in}= V_{en}=5V$		1		mA

Note: Dropout voltage is defined as the input voltage minus the output voltage that produces a 2% change in the output voltage from the value at $V_{IN} = V_{OUT}+2V$ with a fixed load.

Function Description

The BM0123A uses a constant frequency control scheme to provide excellent line and load regulation. Operation can be best understood by referring to the block diagram. At the start of each oscillator cycle, the SR latch is set, which turns on the power switch M1. An artificial ramp is generated to the positive terminal of the PWM comparator A2. When this voltage exceeds the level at the negative input of A2, the SR latch is reset turning off the power switch. The level at the negative input of A2 is set by the error amplifier A1, and is simply an amplified version of the difference between the feedback voltage and the reference voltage of 0.254V. In this manner, the error amplifier sets the correct peak current level to keep the output in regulation. If the error amplifier's output increases, more current is delivered to the output, if it decreases, less current is delivered.

Shutdown

The shutdown pin, SHDN, must not be allowed to float. When the SHDN pin voltage is taken below 0.8V, the internal MOSFET, voltage reference, error amplifier, comparators and biasing circuitry will all be switched off reducing the quiescent supply current to less than 1_uA. If the SHDN pin has a value greater than 1.3V, then the device will be fully enabled and operational. This pin also can be used as a PWM signal from 100Hz to 1kHz to allow brightness control.

Over Voltage Protection

The OVP function is designed to prevent damage to the internal NMOS switching transistor. When the output voltage rises above the OVP threshold voltage, typically 17V, the converter will clamp the output voltage to this level. When the output voltage returns to a value below the OVP threshold, it will automatically resume normal switching operation.

Application Information

Inductor Selection

A 10 μ H inductor is recommended for BM0123A applications. Small size and high efficiency are the major concerns for most BM0123A applications. Inductor with low core losses and small DCR (cooper wire resistance) at 1.4MHz are good choice for BM0123A applications.

Diode Selection

Schottky diodes, with their low forward voltage drop and fast reverse recovery, are the ideal choices for BM0123A applications. The forward voltage drop of a Schottky diode represents the conduction losses in the diode, while the diode capacitance (CT or CD) represents the switching losses. For diode selection, both forward voltage drop and diode capacitance need to be considered. Schottky diodes with higher current ratings usually have lower forward voltage drop and larger diode capacitance, which can cause significant switching losses at the 1.4MHz switching frequency of the BM0123A. A Schottky diode rated at 500mA is sufficient for most BM0123A applications.

Capacitor Selection

The small size of ceramic capacitors makes them suitable for BM0123A applications. X5R and X7R types are recommended because they retain their capacitance over wider voltage and temperature ranges than other types such as Y5V or Z5U. A minimum 1 μ F capacitor for output is required for most applications. Larger input/output capacitor minimizes input/output ripple.

Typical Performance Characteristics




Fig1: Output Current VS Input Voltage




Fig2: Quiescent Supply Current VS Input Voltage




Fig3: Efficiency VS Input Voltage




Fig4: Temperature VS Frequency





Fig4: Temperature VS Output Voltage

SOT-26 Diagram



Symbol	Dimension(in mm)		Dimension(in Inch)	
	min	max	min	max
A	0.787	1.450	0.031	0.057
A1		0.152		0.006
B	1.397	1.803	0.055	0.071
b	0.250	0.559	0.010	0.022
C	2.591	2.997	0.102	0.118
D	2.692	3.099	0.106	0.122
E	0.838	1.041	0.033	0.041
H	0.080	0.254	0.003	0.010
L	0.300	0.610	0.012	0.024